



BOS40

Width: 18.25"
Height: 39.25"
Weight: 50lbs
EPA: 3.94ft²

Bostonian
ordering guide

- 40" Bostonian Luminaire
- 16" Scroll Bracket



Luminaires

ordering logic

model		
BOS40	40" Bostonian	
lens material		
<input type="checkbox"/>	A	acrylic
<input type="checkbox"/>	P	polycarbonate
lens finish		
<input type="checkbox"/>	C	clear
<input type="checkbox"/>	F	frosted
<input type="checkbox"/>	S	seeded
<input type="checkbox"/>	W	white
source		
<input type="checkbox"/>	LED	60 & 90W
<input type="checkbox"/>	QL	55 & 85W Induction
<input type="checkbox"/>	PSMH	50 - 150W
<input type="checkbox"/>	HPS	50 - 150W
<input type="checkbox"/>	CF	13 - 42W
<input type="checkbox"/>	INC	150W
<input type="checkbox"/>	NGO	natural gas
optics		
<input type="checkbox"/>	IND3	indirect type III (LED)
<input type="checkbox"/>	IND5	indirect type V (LED)
<input type="checkbox"/>	DIR2	direct type II (LED)
<input type="checkbox"/>	DIR3	direct type III (LED)
<input type="checkbox"/>	DIR4	direct type IV (LED)
<input type="checkbox"/>	DIR5	direct type V (LED)
<input type="checkbox"/>	SR3	segmented reflector type III
<input type="checkbox"/>	SR4	segmented reflector type IV
<input type="checkbox"/>	SR5	segmented reflector type V
<input type="checkbox"/>	GR3	glass refractor type III
<input type="checkbox"/>	GR5	glass refractor type V
<input type="checkbox"/>	FGCH	frosted glass chimney <i>(n/a w/LED)</i>
<input type="checkbox"/>	3CD	triple candelabra <i>(n/a w/LED)</i>
<input type="checkbox"/>	BL	bare lamp

model (cont)	
BOS40	40" Bostonian
electrical options	
<input type="checkbox"/>	FS fusing
<input type="checkbox"/>	PEC photocell
<input type="checkbox"/>	QRS quartz restrike
<input type="checkbox"/>	IQ lamp/ballast diagnostics
<input type="checkbox"/>	LSP lightning surge protector
<input type="checkbox"/>	PT post top
<input type="checkbox"/>	PM pendant
style options	
<input type="checkbox"/>	<input type="checkbox"/> TRF traditional fitter
<input type="checkbox"/>	<input type="checkbox"/> FLF frog leg fitter
color (see page 33 for additional information)	
<input type="checkbox"/>	BB black
<input type="checkbox"/>	BZ bronze
<input type="checkbox"/>	BG green
<input type="checkbox"/>	BW white
<input type="checkbox"/>	BY gray
<input type="checkbox"/>	RAL RAL _____
<input type="checkbox"/>	OTHER _____

footnotes:

- IND and DIR optics require LED source, LED source requires IND or DIR optics.
- FGCH & 3CD options are optionally energized when SR optics are selected (please consult factory for accommodation).
- Factory suggests that BL option is selected only when a low wattage source is used in conjunction with non-clear lenses.
- Medium socket is standard for all HID sources under 250W.
- LED and CF sources utilize a 120-277 voltage-sensing electronic driver, HID sources utilize a Quad-Tap (120, 208, 240 & 277V) core & coil magnetic ballast, consult factory for 347 or 480V. 12VDC LED drivers are available for solar power assembly integration, consult factory.
- QL induction source shall be supplied at 4000K (CCT), specify if 3000K is required.
- LED source shall be supplied at 4500K (CCT), specify if other color temp. is required (minimum quantities may apply).